Musing upon Information Theory

ISIT Austin, June 13-18, 2010 Te Sun HAN

I. Preliminaries---Information-Spectra

source 1:
$$X =$$

$$3/8 \quad 1/2 \quad 1/8$$

source 2:
$$X'=\left(\begin{array}{cccc} a' & b' & c' \\ & & & \\ 1/2 & 1/8 & 3/8 \end{array}\right)$$
 symbols probabilities $P_{X'}(\cdot)$

probabilities
$$P_{X'}(\cdot)$$

$$X \neq X'$$

Two standpoints: $X \neq X'$ (under renaming

$$X \equiv X'$$

and permutation) $X \equiv X'$ concept of information- spectra!


What is the information-spectrum?

probability information-spectra for X and X' self-information $\log_2 \frac{1}{P_{X'}(X')}, \log_2 \frac{1}{P_{X'}(X')}$

- One information-spectrum for one source
- It is easy to check that the information-spectra are the same for sources X and X'

i.i.d. sequence	probabilities	r	non i.i.d.sequence	
0000	$(\frac{1}{3})^4$	1	1010	$(\frac{1}{3})^4$
0001	$(\frac{1}{3})^3 \frac{2}{3}$	$p(0) = \frac{1}{3},$	1101	$(\frac{1}{3})^3 \frac{2}{3}$
0010	$(\frac{1}{3})^3 \frac{2}{3}$	$n(1) = \frac{2}{-}$	0100	$(\frac{1}{3})^3 \frac{2}{3}$
0011	$(\frac{1}{3})^2(\frac{2}{3})^2$	3	0110	$(\frac{1}{3})^2(\frac{2}{3})^2$
0100	$(\frac{1}{3})^3 \frac{2}{3}$		1011	$(\frac{1}{3})^3 \frac{2}{3}$
0101	$(\frac{1}{3})^2(\frac{2}{3})^2$	renaming	0000	$(\frac{1}{3})^2(\frac{2}{3})^2$
0110	$(\frac{1}{3})^2(\frac{2}{3})^2$	$X \Longrightarrow X'$	0001	$(\frac{1}{3})^2(\frac{2}{3})^2$
0111	$\frac{1}{3}(\frac{2}{3})^3$		1000	$\frac{1}{3}(\frac{2}{3})^3$
1000	$(\frac{1}{3})^3 \frac{2}{3}$		1111	$(\frac{1}{3})^3 \frac{2}{3}$
1001	$(\frac{1}{3})^2(\frac{2}{3})^2$	•	1001	$(\frac{1}{3})^2(\frac{2}{3})^2$
1010	$(\frac{1}{3})^2(\frac{2}{3})^2$	What source	0111	$(\frac{1}{3})^2(\frac{2}{3})^2$
1011	$\frac{1}{3}(\frac{2}{3})^3$	is X' at all?	0010	$\frac{1}{3}(\frac{2}{3})^3$
1100	$(\frac{1}{3})^2(\frac{2}{3})^2$		1110	$(\frac{1}{3})^2(\frac{2}{3})^2$
1101	$\frac{1}{3}(\frac{2}{3})^3$ Fa	r from stanc	ard 1100	$\frac{1}{3}(\frac{2}{3})^3$
1110	$\frac{1}{3}(\frac{2}{3})^3$		0101	$\frac{1}{3}(\frac{2}{3})^3$
1111	$\left(\frac{2}{3}\right)^4$		0011	$(\frac{2}{3})^4$

Let us depict again the information-spectra for these sources X and X':





It is easy to check that both coincide again!



The information spectra remain the same under renaming and permutation!!

Remark 1 (very import observation!):





II. Asymptotic Information-Spectra

general source $\mathbf{X} = \{X^n\}_{n=1}^{\infty}$


 $\frac{1}{n}\log\frac{\frac{1}{P_{X^n}(X^n)}}{P_{X^n}(X^n)}$

Example 1

- 1) i.i.d. source
- 2)Markov source
- 3)ergordic source



AEP
(Asymptotic Equi-Partition)



Example 2


4)mixed source

$$P_{X^n}(\mathbf{x}) = \alpha_1 P_{X_1^n}(\mathbf{x}) + \alpha_2 P_{X_2^n}(\mathbf{x})$$

 X_1^n : i.i.d. $\sim P_1$

 X_2^n : i.i.d. $\sim P_2$

 $H(P_1) \neq H(P_2)$







Quesiotn: How to define "AEP" for general sources?



Information-spectrum approach is useful!



Let me try to show it!




Fundamental tools for information-spectra

¶ lim-sup in probability

p-
$$\limsup_{n\to\infty} Z_n \equiv \inf \left\{ \alpha | \lim_{n\to\infty} \Pr\{Z_n > \alpha\} = 0 \right\}$$

¶ lim-inf in probability

$$\operatorname{p-} \liminf_{n \to \infty} Z_n \equiv \sup \left\{ \beta | \lim_{n \to \infty} \Pr\{Z_n < \beta\} = 0 \right\}$$



lim-sup and lim-inf in probabilities

$$\begin{array}{lll} \operatorname{p-}\lim\sup_{n\to\infty}(Z_n+V_n) & \leq & \operatorname{p-}\limsup_{n\to\infty}Z_n+\operatorname{p-}\limsup\sup_{n\to\infty}V_n \\ \operatorname{p-}\liminf_{n\to\infty}(Z_n+V_n) & \geq & \operatorname{p-}\liminf_{n\to\infty}Z_n+\operatorname{p-}\liminf_{n\to\infty}V_n \\ \operatorname{p-}\limsup_{n\to\infty}(Z_n+V_n) & \geq & \operatorname{p-}\limsup_{n\to\infty}Z_n+\operatorname{p-}\liminf_{n\to\infty}V_n \\ \operatorname{p-}\liminf_{n\to\infty}(Z_n+V_n) & \leq & \operatorname{p-}\limsup_{n\to\infty}Z_n+\operatorname{p-}\liminf_{n\to\infty}V_n \\ \operatorname{p-}\liminf_{n\to\infty}Z_n & \leq & \operatorname{p-}\limsup_{n\to\infty}Z_n \\ \operatorname{p-}\limsup_{n\to\infty}(-Z_n) & = & -\operatorname{p-}\liminf_{n\to\infty}Z_n \\ \operatorname{p-}\limsup_{n\to\infty}Z_n & = \operatorname{p-}\liminf_{n\to\infty}Z_n & = c \\ \end{array}$$


$$\operatorname{p-}\lim\sup_{n\to\infty}Z_n & = \operatorname{p-}\liminf_{n\to\infty}Z_n & = c \\ \operatorname{p-}\lim\sup_{n\to\infty}Z_n & = c \\ \end{array}$$

(limit in probability)

For general source
$$\mathbf{X} = \{X^n\}_{n=1}^{\infty}$$

- ¶ spectral lim-sup: $\overline{H}(\mathbf{X}) = \text{p-}\limsup_{n\to\infty} \frac{1}{n} \log \frac{1}{P_{X^n}(X^n)}$
- ¶ spectral lim-inf: $\underline{H}(\mathbf{X}) = \text{p-} \liminf_{n \to \infty} \frac{1}{n} \log \frac{1}{P_{X^n}(X^n)}$

information-spectrum of X



II. AEP, Strong Converse, and Information-Spectra

¶Definition1¶ (strong converse property)


A general source \mathbf{X} is said to satisfy the strong converse property if, with any given rate R, the optimal coding always yields either $\lim_{n\to\infty} \varepsilon_n = 1$ or $\lim_{n\to\infty} \varepsilon_n = 0$ where ε_n is the decoding error probability.


¶Definition 2 ¶ (generalized AEP)

A general source \mathbf{X} is said to satisfy AEP if there exists a set $T_n^{\varepsilon} \subset \mathcal{X}^n$ such that $P_{X^n}(T_n^{\varepsilon}) \to 1$ and $P_{X^n}(\mathbf{x}) \simeq \exp[-n(\underline{H}(\mathbf{X}) \pm \epsilon)]$ for $\forall \mathbf{x} \in T_n^{\varepsilon}$ $(\forall \epsilon > 0)$

¶Theorem 1¶

one-point spectrum





III. Source Coding, and Information-Spectra

Fixed-length source coding

encoder decoder
$$X^n \longrightarrow \widehat{\mathcal{Y}}_n \longrightarrow \widehat{\mathcal{M}}_n \longrightarrow \widehat{\psi}_n \longrightarrow \widehat{X}^n \equiv \psi_n(\varphi_n(X^n))$$

$$\mathcal{M}_n \equiv \{1, 2, \cdots, M_n\}$$

- coding rate : $\frac{1}{n} \log M_n$
- error probability : $\varepsilon_n \equiv \Pr{\{\hat{X}^n \neq X^n\}}$
- R is achievable $\Leftrightarrow \limsup_{n \to \infty} \frac{1}{n} \log M_n \le R, \lim_{n \to \infty} \varepsilon_n = 0$


(we want here to make R as small as possible)

Definition 3 \P $R_f(\mathbf{X}) = \inf\{R | R \text{ is achievable}\}$

Thorem 2 ¶ (Han & Verdu, 1993)


Optimal coding rate $R_f(\mathbf{X}) = \overline{H}(\mathbf{X})$

information-spectrum of X




IV. Intrinsic Randomness and Information-Spectra

Uniform random number generation (intrinsic randomness)



Formal description (1): intrinsic randomness



- ${f O}$ U_{M_n} : uniform (on ${\cal M}_n$) random variable
 - divergence:

$$D(P||Q) = \sum_{i=1}^{M_n} p_i \log \frac{p_i}{q_i}$$

- random number generation rate : $\frac{1}{n} \log M_n$
- randomness distance : $\rho_n \equiv \frac{1}{n} D(\hat{X}^n || U_{M_n})$
- R is achievable $\Leftrightarrow \liminf_{n\to\infty} \frac{1}{n} \log M_n \ge R, \lim_{n\to\infty} \rho_n = 0$


(we want here to make R as large as possible)

 \P Definition $4\P$ $S_{\iota}^*(\mathbf{X}) = \sup\{R | R \text{ is achievable}\}$

Theorem 3 (Vembu & Verdu, 1995)


Intrinsic randomness : $S_{\iota}^*(\mathbf{X}) = \underline{H}(\mathbf{X})$

information-spectrum of X



V. Resolvability and Information-Spectra

Arbitrary random number generation (resolvability)



Formal description (2): resolvability

encoder
$$\mathbf{X} \equiv \{X^n\}_{n=1}^\infty$$
 (target) is given $U_{M_n} \longrightarrow \varphi_n$ $\hat{\mathcal{X}}^n \equiv \varphi_n(U_{M_n})$ $\hat{\mathcal{X}}^n \equiv \varphi_n(U_{M_n})$ encoder $\hat{\mathcal{X}}^n \equiv \varphi_n(U_{M_n})$ $\hat{\mathcal{X}}^n \equiv \varphi_n(U_{M_n})$ encoder $\hat{\mathcal{X}}^n \equiv \varphi_n(U_{M_n})$

variational distance

 $d(P,Q) = \sum_{i} |p_i - q_i|$

random number coding

rate:
$$\frac{1}{n} \log M_n$$

- •randomness distance : $\sigma_n \equiv d(\hat{X}^n, X^n)$
- R is achievable $\Leftrightarrow \limsup_{n \to \infty} \frac{1}{n} \log M_n \le R, \lim_{n \to \infty} \sigma_n = 0$


(we want here to make R as small as possible)

¶Definition 5 ¶
$$S_r(\mathbf{X}) = \inf\{R | R \text{ is achievable}\}$$

¶THeorem 4 ¶ (Han &Verdu,1993)



information-spectrum of X



VI. Folklore, and Information-Spectra

Let us consider the following "folklore:"

The encoder output $\varphi_n(X^n)$ working at the optimal rate for a source $\mathbf{X} = \{X^n\}_{n=1}^{\infty}$ looks like almost completely random with $n \to \infty$.


Question: How to formally define the "class of sources" and "notion of almost completely random."



In order to solve this problem, we need

Theorems 1, 2, 3 (previous), and Theorem 5 (next).

Three information sources in coding



$$\sharp \ \mathbf{X} = \{X^n\}_{n=1}^{\infty} \quad \text{(source 1)}$$


$$\sharp \ \hat{\mathbf{X}} = \{\hat{X}^n\}_{n=1}^{\infty} \quad (\hat{X}^n = \varphi_n(X^n)) \text{ (source 2)}$$

$$\sharp \ \tilde{\mathbf{X}} = \{\tilde{X}^n\}_{n=1}^{\infty} \quad (\tilde{X}^n = \psi_n(\varphi_n(X^n))) \text{ (source 3)}$$

Theorem 5 ¶ (invariance of information-spectra)


In the process of source coding with decoding error probability $\varepsilon_n \to 0 \ (n \to \infty)$, three information-spectra of \mathbf{X} , $\hat{\mathbf{X}}$, $\tilde{\mathbf{X}}$ asymptotically have the same form.

information-spectra of the same form



¶Corollary 1 ¶(preservation of strong converse property)

In the process of source coding with decoding error probability $\varepsilon_n \to 0 \ (n \to \infty)$, the strong converse property (= AEP) is preserved at the same position.



Pefinition 6 Levy distance between prob. dist.s)

The notion "asymptotically the same form" in Theorem 5:



$$\lim_{n \to \infty} L\left(\frac{1}{n}\log\frac{1}{P_{X^n}(X^n)}, \frac{1}{n}\log\frac{1}{P_{\hat{X}^n}(\hat{X}^n)}\right) = 0$$

$$\lim_{n \to \infty} L\left(\frac{1}{n}\log \frac{1}{P_{X^n}(X^n)}, \frac{1}{n}\log \frac{1}{P_{\tilde{X}^n}(\tilde{X}^n)}\right) = 0$$

• L(U,V) is called Levy distance:= the infimum of all $\mu > 0$ such that, for all reals x,

$$\Pr\{U \le x - \mu\} - \mu \le \Pr\{V \le x\} \le \Pr\{U \le x + \mu\} + \mu$$

Definition 7 ¶ (the notion "almost completely random")

A general source $\mathbf{Z} = \{Z^n\}_{n=1}^{\infty}$ is said to be almost completely random with size M_n if it holds that

$$\lim_{n\to\infty} \frac{1}{n} D(Z^n||U_{M_n}) = 0,$$

where $D(\cdot||\cdot)$ is the divergence, and the limit:

$$\lim_{n\to\infty}\frac{1}{n}\log M_n$$

exists.

¶ Theorem 6 ¶ (Folklore: Han, 2005)

The encoder output $\varphi_n(X^n)$ working at the optimal rate for a "general" source $\mathbf{X} = \{X^n\}_{n=1}^{\infty}$ is almost completely random if and only if \mathbf{X} satisfies the strong converse property (=AEP).

left Remark: A "general" source $\mathbf{X} = \{X^n\}_{n=1}^{\infty}$ affords

"any" nonstationary memory structure, which includes, as very special cases, all ergodic sources.

Hint for the proof:

```
1) part \Leftarrow: Use Theorem 1 (\underline{H}(\mathbf{X}) = \overline{H}(\mathbf{X}))


Theorem 2 (R_f(\mathbf{X}) = \overline{H}(\mathbf{X}))

Theorem 5 (invariance theorem)
```

2) part
$$\implies$$
: Use Theorem 2 $(R_f(\mathbf{X}) = \overline{H}(\mathbf{X}))$
Theorem 3 $(S_L^*(\mathbf{X}) = \underline{H}(\mathbf{X}))$



Folklore looks like a navel of the world of Information-Spectra



VII. Reliability Function, and Information Spectra



Fixed-length source coding (cont.)

encoder decoder
$$X^n \longrightarrow \widehat{Y}^n \longrightarrow \widehat{W}_n \longrightarrow \widehat{X}^n \equiv \psi_n(\varphi_n(X^n))$$

$$\mathcal{M}_n \equiv \{1, 2, \cdots, M_n\}$$

- coding rate : $\frac{1}{n} \log M_n$
- •error probability : $\varepsilon_n \equiv \Pr\{\hat{X}^n \neq X^n\}$
- R is r-achievable $\iff \limsup_{n \to \infty} \frac{1}{n} \log M_n \le R, \lim_{n \to \infty} \frac{1}{n} \log \frac{1}{\varepsilon_n} \ge r$

(we want to make R as small as possible)

exponentially decaying error probability

$$\varepsilon_n \lesssim e^{-nr}$$

$$\lim_{n \to \infty} \frac{1}{n} \log \frac{1}{n} \ge r$$

Reliability function for source coding

Definition 8 ¶ $R_e(r|\mathbf{X}) = \inf\{R|R \text{ is } r\text{-achievable}\}$

¶Theorem 7 ¶ (Reliability function: Han, 2000)


$$R_e(r|\mathbf{X}) = \sup_{R} \{R - \sigma(R) | \sigma(R) < r\}$$

where, $\sigma(R) = \liminf_{n \to \infty} \frac{1}{n} \log \frac{1}{\Pr\left\{\frac{1}{n} \log \frac{1}{P_{X^n}(X^n)} \ge R\right\}}$ information-

spectrum

$$\frac{1}{n} \log \frac{1}{P_{X^n}(X^n)}$$

Hint for the proof (direct part):



• # of sequences in $[R, R + \gamma)$

$$\lesssim e^{-n\sigma(R)}/e^{-nR} \simeq e^{n(R-\sigma(R))} \quad (\sigma(R) < r)$$

 \bullet #of total sequences $\lesssim \sup_{R:\sigma(R) < r} e^{n(R-\sigma(R))}$

Remark 2 (large deviation):

The argument used here is called "information-spectrum slicing," which is a kind of typical large deviation techniques; the slicing would be intuitively understandable.

The "informaton-spectrum slicing" argument

is applicable also to the problems in random number generation, rate-distortion theory, and hypothesis testing, channel coding, etc.

Remark 3:

It is a tradition, given a rate R, to compute the optimal error probabilty ε

Here, given an error probability ε , we compute the optimal rate R. This approach would be easier.

Example 3 (Longo & Sgarro, 1979)

- Let $\mathbf{X} = (X_1, X_2, \cdots)$ be an i.i.d. subject to P on a finite alphabet \mathcal{X}
- Define $\pi_R = \left\{Q \in \mathcal{P}(\mathcal{X}) \middle| \sum_{x \in \mathcal{X}} Q(x) \log \frac{1}{P(x)} \geq R\right\}$ and

$$\inf_{Q \in \pi_R} D(Q||P) = D(Q_R||P)$$


Sanov's theorem

$$\sigma(R) = D(Q_R||P)$$



$$R_e(r|\mathbf{X}) = \sup_{Q:D(Q||P) < r} H(Q).$$

 Q_R : projection of P



Example 4

Let $\mathbf{X} = (X_1, X_2, \cdots)$ be an i.i.d. subject to $P = (p_1, p_2, \cdots)$ on a countably infinite alphabet $\mathcal{X} = \{1, 2, \cdots\}$, where

$$p_i = \frac{c}{(i+1)(\log(i+1))^4}$$
 $(i=1,2,\cdots).$

(heavy tail distribution; finite entropy)

 $\downarrow \!\!\!\downarrow$ Cramer's theorem (with rate function I(x))

$$\sigma(R) = \inf_{x \ge R} I(x) = 0 \quad \text{(for all } R\text{)}$$

↓ Theorem 7

$$R_e(r|\mathbf{X}) = +\infty \text{ (for all } r > 0)$$

any finite rate is not enough for exponentially decaying error probability


Example 5 (nonstationary and nonergodic source)

• Consider a subset $S_n \subset \{0,1\}^n$ such that $|S_n| = 2^{\alpha n}$

$$(0 < \alpha < 1)$$
, and fix $\mathbf{x}_0, \mathbf{x}_1 \in \{0, 1\}^n - S_n \text{ with } \mathbf{x}_0 \neq \mathbf{x}_1$

Define the probability distribution:

$$P_{X^n}(\mathbf{x}) = \begin{cases} 2^{-2\alpha n} & \text{for } \mathbf{x} \in S_n, \\ 2^{-3\alpha n} & \text{for } \mathbf{x} = \mathbf{x}_1, \\ 1 - 2^{-\alpha n} - 2^{-3\alpha n} & \text{for } \mathbf{x} = \mathbf{x}_0, \\ 0 & \text{for } \mathbf{x} \notin S_n \cup \{\mathbf{x}_1, \mathbf{x}_0\}. \end{cases}$$



three-point

Cramer's theorem and Sanov theorem do not work!

$$\sigma(R) = \begin{cases} 0 & \text{for} & R \leq 0, \\ \alpha & \text{for} & 0 < R \leq 2\alpha, \\ 3\alpha & \text{for} & 2\alpha < R \leq 3\alpha, \\ +\infty & \text{for} & 3\alpha < R \end{cases} \xrightarrow{R_e(r|\mathbf{X})} = \begin{cases} \alpha & \text{for} & r > \alpha, \\ 0 & \text{for} & 0 < r \leq \alpha. \end{cases}$$

$$Theorem 7$$

$$\sigma(R) = \begin{cases} 0 & \text{for} & R \leq 0, \\ \alpha & \text{for} & 0 < R \leq 2\alpha, \\ 0 & \text{for} & 0 < r \leq \alpha. \end{cases}$$

$$Theorem 7$$

VIII. Hypothesis Testing, and Information-Spectra


Hypothesis testing

$$\bullet$$
 $\mathbf{X} = \{X^n\}_{n=1}^{\infty}$ and $\overline{\mathbf{X}} = \{\overline{X}^n\}_{n=1}^{\infty}$ are general sources

 $H: \mathbf{X}$ (null hypothesis) $\overline{H}: \overline{\mathbf{X}}$ (alternative hypothesis)

- **e**acceptance region A_n :
- •decision rule:

if $\mathbf{x} \in \mathcal{A}_n$, output H:
if $\mathbf{x} \notin \mathcal{A}_n$, output \overline{H} :



error probabilities:

$$\mu_n \equiv \Pr\{X^n \notin \mathcal{A}_n\}$$
 (type I error probability) $\lambda_n \equiv \Pr\{\overline{X}^n \in \mathcal{A}_n\}$ (type II error probability)

• Let $B_e(r|\mathbf{X}||\mathbf{\overline{X}})$ denote the supremum of rates R such that $\mu_n \lesssim e^{-nr}$, $\lambda_n \lesssim e^{-nR}$

(we want to make R as large as possible)


r: fixed

¶Theorem 8 ¶ (Testing power function: Han, 2000)

$$B_e(r|\mathbf{X}||\overline{\mathbf{X}}) = \inf_R \{R + \eta(R)|\eta(R) < r\}$$

where

$$\eta(R) = \liminf_{n \to \infty} \frac{1}{n} \log \frac{1}{\Pr\left\{\frac{1}{n} \log \frac{P_{X^n}(X^n)}{P_{\overline{X}^n}(X^n)} \le R\right\}}$$




Radon-Nikodym derivative informationspectrum

$$\frac{1}{n}\log\frac{P_{X^n}(X^n)}{P_{\overline{X}^n}(X^n)} \quad \longleftarrow$$

 $ightharpoonup rac{1}{n} \log rac{P_{X^n}(X^n)}{P_{\overline{X}^n}(X^n)}
ightharpoonup rac{normalized}{\log likelihood-ratio}$

Hint for the proof (direct part):



Example 6 (Hoeffding, 1965)

Let $\mathbf{X} = \{X^n\}_{n=1}^{\infty}, \overline{\mathbf{X}} = \{\overline{X}^n\}_{n=1}^{\infty}$ be i.i.d. subject to P, \overline{P} , on a finite alphabet χ

Define $\kappa_R = \left\{ Q \in \mathcal{P}(\mathcal{X}) \left| \sum_{x \in \mathcal{X}} Q(x) \log \frac{P(x)}{\overline{P}(x)} \le R \right. \right\}$ and

$$\inf_{Q \in \kappa_R} D(Q||P) = D(Q_R||P)$$




↓ Sanov's theorem

 Q_R : projection of P

$$\eta(R) = D(Q_R||P)$$

Theorem 8

$$B_e(r|\mathbf{X}||\overline{\mathbf{X}}) = \inf_{Q:D(Q||P) < r} D(Q||\overline{P}).$$



Example 7 (Gaussian sources)

Let $\mathbf{X} = \{X^n\}_{n=1}^{\infty}, \ \overline{\mathbf{X}} = \{\overline{X}^n\}_{n=1}^{\infty} \ \text{be i.i.d. sources}$ subject to Gaussian distributions $N(\kappa, \sigma^2)$, $N(\overline{\kappa}, \sigma^2)$:

$$P_{\kappa}(x) = \frac{1}{\sqrt{2\pi}\sigma} e^{-\frac{(x-\kappa)^2}{2\sigma^2}}, \ P_{\overline{\kappa}}(x) = \frac{1}{\sqrt{2\pi}\sigma} e^{-\frac{(x-\overline{\kappa})^2}{2\sigma^2}}.$$


Cramer's theorem

$$\eta(R) = \inf_{x \le R} I(x) = \min \left\{ [a - R]^+, \frac{\sigma^2 (R - a)^2}{2(\kappa - \overline{\kappa})^2} \right\} \quad (a = D(P_{\kappa} || P_{\overline{\kappa}}))$$



 $igcup_{B_e(r|\mathbf{X}||\overline{\mathbf{X}})}$ Theorem 8

$$B_e(r|\mathbf{X}||\overline{\mathbf{X}}) = (\sqrt{r} - \sqrt{a})^2 \mathbf{1}[r \le a]$$



Example 8 (nonstationary and nonergodic source)

- \bullet Let P_{X^n} be the source (null) as specified as in Example 6, and $P_{\overline{X}^n}$ be another source (alternative) defined by $P_{\overline{X}^n}(\mathbf{x}) = 2^{-n} \ (\forall \mathbf{x} \in \{0, 1\}^n).$
- Cramer's theorem and Sanov theorem do not work! but we can directly calculate:

$$\eta(R) = \begin{cases} +\infty & \text{for} & R < 1 - 3\alpha, \\ 3\alpha & \text{for} & 1 - 3\alpha \le R < 1 - 2\alpha, \\ \alpha & \text{for} & 1 - 2\alpha \le R < 1, \\ 0 & \text{for} & 1 \le R. \end{cases}$$

$$\downarrow \text{Theorem 8}$$

$$B_e(r|\mathbf{X}||\overline{\mathbf{X}}) = \begin{cases} 1 - \alpha & \text{for} & r > \alpha, \\ 1 & \text{for} & 0 < r \le \alpha. \end{cases}$$

$$1 - \alpha$$

IX. Generalized Hypothesis Testing, and Information-Spectra




Generalized hypothesis testing

$$\mathbf{X} = \{X^n\}_{n=1}^{\infty}$$
 is a general source, and $\overline{\mathbf{G}} = \{\overline{G}_n\}_{n=1}^{\infty}$ is a sequence of nonnegative measures

- $H: \mathbf{X}$ (nul hypothesis) $\overline{H}: \overline{\mathbf{G}}$ (alternative measure)
- lacktriangle acceptance region A_n :
- decision rule:

if
$$\mathbf{x} \in \mathcal{A}_n$$
, output H :
if $\mathbf{x} \notin \mathcal{A}_n$, output \overline{H} :



error probability (measure):

$$\mu_n \equiv \Pr\{X^n \notin \mathcal{A}_n\}$$
 (type I error probability) $\lambda_n \equiv \overline{G}_n(\mathcal{A}_n)$ (type II measure)

• Let $B_e(r|\mathbf{X}||\mathbf{G})$ denote the supremum of rates R such that $\mu_n \lesssim e^{-nr}$, $\lambda_n \lesssim e^{-nR}$

(we want to make R as large as possible) r: fixed

¶Theorem 9 ¶ (generalized testing power function: Han,1998)

$$B_e(r|\mathbf{X}||\overline{\mathbf{G}}) = \inf_{R} \{R + \eta_{\overline{G}}(R)|\eta_{\overline{G}}(R) < r\}$$

where
$$\eta_{\overline{G}}(R) = \liminf_{n \to \infty} \frac{1}{n} \log \frac{1}{\Pr\left\{\frac{1}{n} \log \frac{P_{X^n}(X^n)}{\overline{G}_n(X^n)} \le R\right\}}$$

Radon-Nikodym derivative

Hypothesis testing and source coding

• As an alternative measure $\overline{\mathbf{G}} = \{\overline{G}_n\}_{n=1}^{\infty}$, consider the counting measure $\overline{\mathbf{C}} = \{\overline{C}_n\}_{n=1}^{\infty}$ defined by $\overline{C}_n(\mathcal{A}_n) = |\mathcal{A}_n|$


 we can establish one-to-one correspondence between source coding and hypothesis testing



source coding

hypothesis testing

correctly decoded set



acceptance region

decoding error probability — type I error probability

of correctly decoded ___ type II measure sequences

Thus

one-to-one correspondence between

hypothesis testing and source coding holds:

Therefore, we have a formula connecting souece coding and hypothesis testing:

¶Theorem10 (Han,1998) ¶

$$R_e(r|\mathbf{X}) = -B_e(r|\mathbf{X}||\overline{\mathbf{C}})$$

The proof:

$$\lambda_n = \overline{C}_n(\mathcal{A}_n) = |\mathcal{A}_n| = M_n = e^{nr_n}$$
 where $r_n = \frac{1}{n} \log M_n$

Thus,
$$\liminf_{n\to\infty}\frac{1}{n}\log\frac{1}{\lambda_n}=-\limsup_{n\to\infty}r_n,$$

which means $R_e(r|\mathbf{X}) = -B_e(r|\mathbf{X}||\overline{\mathbf{C}})$

Theorem 11: another proof of Theorem 7

$$R_e(r|\mathbf{X}) = \sup_{R} \{R - \sigma(R) | \sigma(R) < r\}$$

The proof:

It is easy to check that $\eta_{\overline{C}}(R) = \sigma(-R)$.

Then, Theorem 9 implies

$$B_e(r|\mathbf{X}||\overline{\mathbf{C}}) = -\sup_{R} \{R - \sigma(R)|\sigma(R) < r\}$$

Finally, use Theorem 10.

In a similar way, we have formulas connecting source coding and hypothesis testing:

$$R_f(\mathbf{X}) = -B(\mathbf{X}||\overline{\mathbf{C}}) = \overline{H}(\mathbf{X})$$

$$R_f(\varepsilon|\mathbf{X}) = -B_f(\varepsilon|\mathbf{X}||\overline{\mathbf{C}}) = \inf\{R|F(R) \le \varepsilon\}$$

where
$$F(R) = \limsup_{n \to \infty} \Pr\left\{ \frac{1}{n} \log \frac{1}{P_{X^n}(X^n)} \ge R \right\}$$

Hypothesis testing and the world of Information-spectra

the world of ergodic sources

source coding

hypothesis testing

generalized hypothesis testing

Conclusion

Information-spectrum approach provides conceptually insightful viewpoints in musing on Information Theory!

Thank you!

reference book:

Te Sun Han

Information-Spectrum Methods in Information Theory,

Springer, 2003